



MESSTECHNIK

PCE GmbH • Bölgenweg 6 • 77855 Achern

Telefon (07841) 5373 – Telefax (07841) 9271  
info@pce-achern.de

## *Puls Generator*



**Use:** Test of electrical- and electronics assemblies in the automobile industry  
Employment in development and quality assurance

**Spezification:** Output frequency 0-20 HZ, digital display 0.00 - 20.00 HZ  
Pulse time 1 -100 ms, digital display 1.0 – 100.0 ms  
Input voltage 10 - 30 VDC  
Output current max. 2A  
Number of exits = 1  
Pulse time and frequency over ten-course potentiometers adjustable  
Pulse time over potentiometers adjustable  
Frequency range continuous from 0.1 to 20 cycles per second adjustable  
In the case of change of the frequency the pulse time is kept constant  
Frequency alternatively over potentiometers or similar input voltage 0-5V adjustable

**Testset:** Power supply      Puls Generator      Test specimen

